


Use of Electrochemical Impedance Spectroscopy and in-situ XRD for characterization of cathodes for Li-Sulfur batteries

Dr. Norbert Wagner, Natalia A. Cañas, Kei Hirose and
K. Andreas Friedrich

German Aerospace Center (DLR)
Institute for Technical Thermodynamics, Stuttgart, Germany



International Workshop on
Impedance Spectroscopy

September 26-28 2012, Chemnitz, Germany



Knowledge for Tomorrow



Presentation outline

- Introduction and motivation: Lithium-Sulfur (Li-S) batteries
- Li-S battery at DLR: cathode fabrication
- Application of in-situ XRD and EIS during cycling
- Conclusion and outlook



Motivation

Why Li-Sulfur batteries?


- High theoretical capacity (1675 mAh/g) and specific energy density (2500 Wh/kg)
- Environmental friendliness
- Low cost and availability of sulfur
- Wide temperature range of operation
- Intrinsic protection mechanism from overcharge



Motivation

Why Li-Sulfur batteries?

- High theoretical capacity (1675 mAh/g) and specific energy density (2500 Wh/kg)
- Environmental friendliness
- Low cost and availability of sulfur
- Wide temperature range of operation
- Intrinsic protection mechanism from overcharge






But still...


- High degradation during cycling
- No complete understanding of degradation mechanisms and structural modifications during charge and discharge



Schematic representation of a Li-sulfur battery



$$x = 4 - 8$$




- High order Li-polysulfides (Li_2S_x $x = 4-8$) are soluble in the electrolyte and migrate to the anode avoiding dendrite growth
- During recharging lithium ions are plated back onto the anode and sulfur oxidize back to S_8




Cathode production technique at DLR-TT

Suspension-spray machine




- Nozzle with extern mixing of air and suspension
- Cathode mixture: Sulfur, Carbon Black and PVDF (50:40:10, wt.%).
Solvents: Ethanol and DMSO

**Sprayed
cathode**





5 x 5 cm²



In-situ X-Ray diffraction

Objective:

To monitor the crystalline reaction products of the cathode and the structural changes during cycling




- 1) Anode plate
- 2) Polymer gasket
- 3) Insulator plastic tube
- 4) Spring
- 5) Al-anode collector


6) Anode: lithium
7) Separator (Celgard 2500) impregnated with electrolyte (1M LiPF_6 in TEGDME)

8) Cathode

- 9) Cathode plate
- 10) Al- or Be-window
- 11-12) Holes for banana jacks




Experimental XRD results



In-situ X-ray diffraction data collected during discharging of Li-S battery at a rate of 300 mA g^{-1}

Average discharge capacity is $1276 \text{ mAh g}_{\text{sulfur}}^{-1}$


First discharge step



- a) reaction of sulfur to high order polysulfides (blue)
- b) reactions of high order polysulfides (gray)
- c) formation of Li_2S (red)



Experimental XRD results




In-situ X-ray diffraction data collected during charging of Li-S battery at a rate of 300 mA g^{-1}

Average charge capacity is $1283 \text{ mAh g}_{\text{sulfur}}^{-1}$



First charge step



c) reaction of Li_2S (blue)

b) reactions of high order polysulfides (gray) and

a) formation of sulfur (red).



EIS during cycling


Objective: investigation of physical and chemical processes during cycling

Electrochemical cycling

- Galvanostatic
- Current density: 300 mAh g_{Sulfur}⁻¹
- Charge/discharge end potential:
2.8 V und 1.5 V

EIS:


- Frequencies from 1 MHz to 60 mHz
- Potentiostatic excitation: 5 mV
- Impedance spectra were measured in 50 mC equidistant intervals
- 2-Electrodes configuration




Swagelok-cell (EIS measurements)




Overview EIS during first battery cycling




1. Discharge




Changes in the resistances and the processes




1. Charge



Model for Li-S Battery




Equivalent circuit







Model	Chemical and physical cause
R_0	Ohmic resistance
R_1 - CPE_1	Anode charge transfer
R_2 - CPE_2	Cathode process: charge transfer of sulfur intermediates
R_3 - CPE_3	Cathode process: reaction and formation of S_8 and Li_2S
R_4 - CPE_4	Diffusion

First discharge step

Modelling results




Model	Chemical and physical cause
R_0	Ohmic resistance
R_1 - CPE_1	Anode charge transfer
R_2 - CPE_2	Cathode process: charge transfer of sulfur intermediates
R_3 - CPE_3	Cathode process: reaction and formation of S_8 and Li_2S
R_4 - CPE_4	Diffusion





First discharge step

Modelling results



Model	Chemical and physical cause
R_0	Ohmic resistance
R_1 - CPE_1	Anode charge transfer
R_2 - CPE_2	Cathode process: charge transfer of sulfur intermediates
R_3 - CPE_3	Cathode process: reaction and formation of S_8 and Li_2S
R_4 - CPE_4	Diffusion




Maximum due to high concentration of soluble polysulfides

Ohmic resistance of the cell is influenced by the concentration of polysulfides





First discharge step

Modelling results



Model	Chemical and physical cause
R_0	Ohmic resistance
R_1 - CPE_1	Anode charge transfer
R_2 - CPE_2	Cathode process: charge transfer of sulfur intermediates
R_3 - CPE_3	Cathode process: reaction and formation of S_8 and Li_2S
R_4 - CPE_4	Diffusion




Decrease R_2
 Charge transfer on the cathode surface is favored by decreasing order of polysulfides

Building of non conductive Li_2S avoid the further resistance decrease





First discharge step

Modelling results



Model	Chemical and physical cause
R_0	Ohmic resistance
R_1 - CPE_1	Anode charge transfer
R_2 - CPE_2	Cathode process: charge transfer of sulfur intermediates
R_3 - CPE_3	Cathode process: reaction and formation of S_8 and Li_2S
R_4 - CPE_4	Diffusion



R_3 : appears when:


- S_8 solid film disappears
- Li_2S solid film forms

R_4 : the diffusion of species may be affected by R_3




First charge step


Modelling results




Model	Chemical and physical cause
R_0	Ohmic resistance
R_1 - CPE_1	Anode charge transfer
R_2 - CPE_2	Cathode process: charge transfer of sulfur intermediates
R_3 - CPE_3	Cathode process: reaction of Li_2S and formation of S_8
R_4 - CPE_4	Diffusion




In general:
Lower resistances
than by discharging



Maximum due to
high concentration
soluble polysulfides





Decrease of charge
transfer resistance due to
reaction of non conductive
 Li_2S to high order
polysulfides and S_8




R_3 : dissolution of Li_2S
Lower resistance at
100 % DOC due to
low formation of S_8



Cycling degradation (DOD=100%)





Resistance
due to
formation of
Li₂S



1-20: decrease due to less formation Li₂S
20- 50: formation of stable isolated film?



Cycling degradation (DOD=100%)





Decrease of
discharge
capacity




Reduction of
charge transfer
on cathode
surface

Uncompleted
reaction to Li₂S

Morphological changes in the cathode: less
non-conductive material



Cycling degradation





Ohmic resistance and anode charge transfer resistance stabilizes after approx.. 15 cycles



Conclusions and outlook

- EIS was performed at different depth of discharge and charge for the first cycle of lithium-sulfur (Li-S) batteries
- The mechanisms of Li-S battery aging during cycling were reviewed for fifty cycles
- An equivalent electrical circuit is proposed to simulate the electrochemical processes and to quantify their impedance contributions



- A suitable cell for in-situ XRD analysis was designed and reactions products (S_8 and Li_2S) were monitored during cycling

This work highlights the importance of in-situ studies and the combination of XRD and EIS techniques to reveal new insights into Li-S batteries



Thank you for your Attention !



EIS from 1 MHz – 1 mHz

